


DESIGNED TO MOVE [YOU]

JWM90A OUICK REFERENCE GUIDE



ONE R F100TH • 12:00** ZONE

GENSEN

BLUE

ALARM

ы The ZONE indicator shows which zone is actively being displayed and controlled by the headunit.

MULTI-SOURCE ZONES: If Zone A is in AM, FM, BT, FRONT AUX or REAR AUX mode, the multi-source function cannot be activated. Zone B and Zone C source mode will follow Zone A.


(b)

If Zone A is in DISC, USB, COAXIAL, OPTICAL, HDMI IN or HDMI ARC mode, the following sources are selectable for Zone B: AM, EM, BT, FRONT AUX, REAR AUX as well as the current active Zone A source. Zone C source mode will follow Zone B.

If Zone A and Zone B are both set to DISC, USB, COAXIAL, OPTICAL, HDMI IN, or HDMI ARC mode, the following sources are selectable for Zone C: AM, FM, B FRONT AUX, REAR AUX as well as the current active Zone A/B source. AM. FM. BT.

stored channel.

Multi-source Zone Table		
Zone A	Zone B	Zone C
AM, FM, BT, FRONT AUX or REAR AUX	Same as Zone A	Same as Zone A
DISC, USB, COAXIAL, OPTICAL, HDMI IN or HDMI ARC	AM, FM, BT, FRONT AUX, REAR AUX, or same as Zone A	Same as Zone B (AM, FM, BT, FRONT AUX, REAR AUX)
DISC, USB, COAXIAL, OPTICAL, HDMI IN or HDMI ARC	Same as Zone A	AM, FM, BT, FRONT AUX, REAR AUX, or same as Zone A/B





stored

NOTE: Up to 18 FM & 12 AM channels can be

stations in your area.

knob to select.

